



Digital
System **DS**

Phone Program Record Form





Table of Contents

About the Program Record Form

General Programming Tips

Entering the Program Mode

Entering a Program

Entering Data, Erasing Mistakes, and Moving Through Options

Saving and Exiting

Programs

Program 1 - Class of Service

Program 2 - Intercom Signaling

Program 3 - Miscellaneous System Features

Program 4 - System Timers

Program 5 - PBX Trunk Access Codes

Program 6 - Toll Restriction

Program 7 - Music, External Paging, Relays

Program 8 - System Messages

Program 10 - Line Port Characteristics

Program 11 - Line Groups

Program 12 - Line Features

Program 14 - Extension Port Characteristics

Program 15 - Programming Access Level

Program 16 - Line and Line Group Access

Program 17 - Key Assignments

Program 18 - Extension Features (Part I)

Program 18 - Extension Features (Part II)

Program 19 - Extension Hunt Groups

Program 20 - System Initialization



- In **Edit** ⇨ **Preferences** ⇨ **General**, set the following:
 - **Default Magnification** = Fit Width
 - **Display Splash Screen at Startup** = Disabled (box not checked)
 - **Display Open Dialog Box at Startup** = Disabled (box not checked)
- For easiest reading on-screen, select **View** ⇨ **Fit Width** (or **Ctrl K**). This option is automatically enabled if you set the *Default Magnification* in General Preferences as described above.
- To return to the opening screen at any time, press **Home**.
To scroll up or down on a page, press **PageDown** or **PageUp**.
To navigate between pages, press **→** or **←**.
- To increase the speed with which your Acrobat files load, try one of the following:
 - In **Windows 3.1**, add *ACROREAD.EXE* to your **Startup Group** (with the Run Minimized box checked).
 - In **Windows 95**, add *ACROREAD.EXE* to the **Windows\Start Menu\Programs\StartUp** folder (with Run Minimized selected).
You'll have to maximize the first Acrobat file you run.



- Provides on-line viewing and printing.
- Extensive search and navigation capabilities.
- Ensures more timely turnaround of documents.
- When we provide an Acrobat manual with a product (e.g., Nitsuko TAPI Driver), you are assured of having the most up-to-date manual available.
- With the installation of a PC fax/modem, it makes faxing of any brochure, user guide, proposal or manual quick and easy.
- Acrobat Reader programs for Macintosh, DOS and UNIX platforms also can be provided, if required.
- For Technical Support for the Acrobat Reader, contact:

Adobe Systems, Inc.

1585 Charleston Road

P.O. Box 7900

Mountain View, CA 94039-7900

Telephone Number: 415-961-4400

Adobe FaxY1 (technical/product information by fax): 206-628-5737

Adobe Electronic Bulletin Board (on-line information): 206-623-6984

URL: <http://www.adobe.com>

- To return to the opening screen, press the **HOME** key.

About the Program Record Form

The Program Record Form lets you record the way you configure a customer's DIGITAL SYSTEM and shows you how to enter the configuration data into system memory. For each program in the system, there is a form (grid) for recording the program's configuration data codes. Next to each grid are instructions for entering the data codes into system memory from a system programming extension (e.g., a display phone connected to port 00, initially extension 300).

You'll find the configuration data codes in the DIGITAL SYSTEM Administrator's Programming Guide (P/N N1872ADG**). Simply turn to a program and look for the heading, **Filling Out the Program Record Form**. The data codes for each feature option are underneath.

See also *How to Use Part II (Customizing the System)* in the DIGITAL SYSTEM Administrator's Programming Guide

General Programming Tips

There are four basic steps to entering data codes into system memory. Once you become familiar with them, you will not need to continually refer to the specific entry instructions with each program.

To enter data codes into memory:

1. Enter the program mode from the port 00 phone (initially extension 300) or from another system programming extension (see Program 15).
2. Enter a program.
3. Enter data using the dialpad, erase mistakes, and move through the program's feature options.
4. Save and Exit.

Note: When you program the system for the first time, run Program 20 before any others to ensure that the factory set values are in place.

Entering the Program Mode

To enter the program mode from the port 00 phone or another system programming extension (see Program 15):

1. Do not lift the handset.
2. Press # key.
3. Dial SP.

The code SP stands for "System Program" and is 77 on the dialpad.

4. Dial 5312.

The code 5312 is the DIGITAL SYSTEM password.

5. Press #.

If you leave the system in the program mode too long without pressing a key or dialing a code, you'll hear reorder (fast busy) tone, and the system automatically exits the program mode.

Entering a Program

To enter a program after you enter the program mode:

1. Press the program's key.

-Keys 1-20 give you access to programs 1-20. Keys 1-5 are on the left, keys 6-10 are on the right, keys 11-16 are directly below the dial pad. The HOLD (Program 17), CONF (Program 18), MIC/DND (Program 19), and ICM (Program 20) keys are in the last row of keys. Note: Program numbers 9 and 13 are not used.

Entering Data, Erasing Mistakes and Moving Through Options

To enter data after you enter a program:

1. Dial the data.
2. Press the # key.

This step stores the data and moves you to the next feature option.

For example, to enter the data code Y:

1. Dial Y, which is 9 on the dialpad.
2. Press #.

When you dial data for the last feature option in a program and press #, you exit the level you are working in and return to the previous level. In some cases, "returning to the previous level" means you exit the program and do not have to press SAVE to exit the program (see below).

To erase a mistake (in most cases):

1. Dial * after you dial the mistake but before you press # to store it.

If you make an invalid entry and press #, you will hear reorder (fast busy) tone. You can dial * (in most cases) during the reorder tone and re-enter the data.

To accept the data on the display and move to the next feature option:

1. Press the # key.

Saving and Exiting

To save and exit after entering data:

1. Press the SAVE key.

Pressing SAVE moves you out of a program, one level at a time. You may have to press SAVE several times to exit all the way out.

Note: Some instructions in the Program Record Form are abbreviated.

When You See:

It Means This:

- | | |
|-------------------------|----------------------------------------------------|
| Dial data + # | Enter the system program information, then press # |
| SAVE | Press SAVE |
| DIAL | Press DIAL |

Program 1 - Class of Service

COS	Only Intercom Calls at Night	Off-Premise Call Forward	Break-In (Intrusion)	Camp-On (Busy Extension)	Internal Call Forward	System Speed Dial	Toll Restriction Level	Only Local Calls (Day/Night)	Only Local Calls at Night	Extended Ring	Privacy	Callback Priority	Direct Trunk Access/Camp-On	All Call Page	Page Zone 1 Access	Page Zone 2 Access	Page Zone 3 Access	Silent Monitor	No Single Line Flash/ACD Supervisor	Single Ring for ASI/OPX	Only CO Call FWD to VX	
00																						
01																						
02																						
03																						
04																						
05																						
06																						
07																						
08																						
09																						
10																						
11																						
12																						
13																						
14																						
15																						
16																						
17																						
18																						

Cont'd next page

Program 1 - Class of Service (cont'd)

COS	Only Intercom Calls at Night	Off-Premise Call Forward	Break-In (Intrusion)	Camp-On (Busy Extension)	Internal Call Forward	System Speed Dial	Toll Restriction Level	Only Local Calls (Day/Night)	Only Local Calls at Night	Extended Ring	Privacy	Callback Priority	Direct Trunk Access/Camp-On	All Call Page	Page Zone 1 Access	Page Zone 2 Access	Page Zone 3 Access	Silent Monitor	No Single Line Flash/ACD Supervisor	Single Ring for ASI/OPX	Only CO Call FWD to VX	
19																						
20																						
21																						
22																						
23																						
24																						
25																						
26																						
27																						

To enter Program 1 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 1.
3. Dial COS number + #.
4. To accept the displayed data: #.

OR

- To change the displayed data: Dial data + #.
*To erase data before pressing #: Press *.*
5. Repeat step 4 until done.
If you finish and do not see, "COS. NO.": SAVE.
 6. Select an option:
 - To program another COS: Go to step 3.
 - To exit Program 1: SAVE.
 - To enter another program after exiting: Press its key.
 - To exit program mode: SAVE twice.

Program 2 - Intercom Signaling

Feature Name	Feature Data
Call Wait Tones	
Handsfree Reply	
Voice-Announced Calls	
Auto Handsfree	

To enter Program 2 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 2.
3. To accept the displayed data: #.

OR

- To change the displayed data: Dial data + #.
*- To erase data before pressing #: Press *.*
4. Repeat step 3 for all data.
If you finish and do not see, "SAVE TO EXIT": SAVE.
 5. Select an option:
 - To enter another program: Press its key.
 - To exit program mode: SAVE.

Program 3 - Miscellaneous System Features

Feature Name	Feature Data							
# Operators								
Oper. 01 Ext.								
Oper. 02 Ext.								
Oper. 03 Ext.								
Oper. 04 Ext.								
# System Speed Dial Digits								
Side Tone Test Digit								

Feature Name	Feature Data							
Voice Mail								
Voice Mail Master Ext.								
Dial-Out # in Speed Dial								
Dial 1 Before Area Code								
Walking COS Security Code								
Play MOH on Transfer								
AUX Port's Baud Rate								

To enter Program 3 data:

1. Enter program mode.
 # + dial 775312 + #.
2. Press key 3.
3. To accept the displayed data: #.
 OR
 To change the displayed data: Dial data + #.
 - To erase data before pressing #: Press *.
4. Repeat step 3 for all data.
 If you finish and do not see, "SAVE TO EXIT": SAVE.
5. Select an option:
 - To enter another program: Press its key.
 - To exit program mode: SAVE.

Note: Before a number can be entered as the Voice Mail Master Extension, the VX (Voice Mail) prompt in Program 18 must be set to Y(es) and UCD group programming must be completed.

Program 4 - System Timers

Timer Number	Timer Name	Duration			
01	Park Orbit				
02	Hold Recall				
03	Camp-On				
04	Line Response				
05	Modem Reserve				
06	# Ring Before Recall				
07	# Delayed Rings				
08	Flash Response				
09	Dial Tone Detect				
10	Make				
11	Break				
12	Interdigit				

To enter Program 4 data:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 4.

3. Dial Timer number + #.

4. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

*To erase data before pressing #: Press *.*

5. Repeat steps 3-4 for remaining timers.

6. Select an option:

- To exit Program 4: SAVE.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE twice.

Program 5 - PBX Trunk Access Codes

ID Number	PBX Access Code	
01		
02		
03		
04		
05		
06		
07		
08		
09		
10		
11		

To enter Program 5 data:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 5.

3. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

- To enter a wild card: DIAL + dial X (9) + #.

*- To erase data: Press * + #.*

4. Repeat step 3 for all data.

If you finish and do not see, "SAVE TO EXIT": SAVE.

5. Select an option:

- To enter another program: Press its key.

- To exit program mode: SAVE.

Program 6 - Toll Restriction

Before you fill in data, either use the Copy and Paste commands to make additional copies of the Toll Restriction forms for each Toll Restriction level you wish to customize or print copies of the blank forms. You may not need to use all three forms for each level.

Toll Level	Active Dial Pad	Special N11 Dialing	0 + Dialing	International Dialing	Equal Access Dialing	1 + NXX Dialing	Allow or Deny (See Table #1)	NXX Dialing	Allow or Deny (See Table #2)	NPA Dialing	Allow or Deny (See Table #3)	6-Digit Analysis

Table 1: Allow/Deny NNX Codes For Toll Calls					

Table 2: Allow/Deny NNX Codes for Local Calls					

Table 3: Allow/Deny NPA Codes					

Program 6 - Toll Restriction (cont'd)

Toll Level:	Table 4: Allow/Deny Codes For Area Code:					

Table 5: Allow/Deny Codes For Area Code:					

Table 6: Allow/Deny Codes For Area Code:					

Table 7: Allow/Deny Codes For Area Code:					

Cont'd next page

Program 6 - Toll Restriction (cont'd)

Toll Level:	Table 8: Allow/Deny Codes For Area Code:					

Table 9: Allow/Deny Codes For Area Code:					

Table 10: Allow/Deny Codes For Area Code:					

Table 11: Allow/Deny Codes For Area Code:					

Cont'd next page

Program 6 - Toll Restriction (cont'd)

Toll Level:	Table 12: Allow/Deny Codes For Area Code:					

Table 13: Allow/Deny Codes For Area Code:					

To enter Program 6 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 6.
3. For first-time programming or to initialize (reset) toll levels: Dial I + Y. Otherwise, go to step 5.
To stop initialization after dialing I: Dial N + go to step 5.
4. To allow the system to accept the new NPA codes, at the prompt "NEW DIAL PLAN-N", dial Y.
5. Dial P to program toll levels.
Re-order tone means: Go to step 1 and initialize in step 3.
6. Dial toll level + #.
7. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

*- To erase data before pressing #: Press *.*

- ADD-DELETE-LIST means you can enter Table data. Use a-c for Tables 1 through 3. Use the steps on the following page for Tables 4 through 13.

- a. Dial A, D, or L. Or, to exit the table at this point: # and go to beginning of step 7.
- b. To add/delete: Dial codes.

OR

To list more or exit list: # + go to step 7a.

- c. To save and exit table: # + go to beginning of step 7.

OR

To save and go to "ADD-DELETE-LIST:" SAVE + go to step 7a.

8. Repeat step 7 for all data.

If you finish and do not see, "TOLL LEVEL": Press # until you see it.

Program 6 - Toll Restriction (cont'd)

9. Select an option:

- *To program another level: Go to step 6.*
- *To exit Program 6: SAVE.*
 - *To enter another program after exiting: Press its key.*
- *To exit mode: SAVE twice.*

To use the 6-Digit Analysis Tables (4 - 13) when you see ADD-DELETE- LIST on the display:

1. Dial A, D, or L.

OR

Press # to exit the table (and Program 6).

2. Dial the area code intended for 6-digit analysis.

If you selected "Listing" in step 1, the system lists the codes now, four at a time. To see more codes or exit at the end of the list, press # and return to step 1. Steps 3-6 do not apply to listing.

3. Dial A for an Allow Table of NXX codes.

OR

Dial D for a Deny Table of NXX codes.

4. Dial codes to be added or deleted.

5. Select an option:

- *To save and go to "ADD-DELETE-LIST" for another area code: SAVE + Go to step 1.*
- *To save and exit toll level: # + Go to step 6 on the previous page.*
- *To save and exit Program 6: SAVE three times.*
 - *To enter another program after exiting: Press its key.*
- *To SAVE and exit program mode: SAVE four times.*

Program 7 - Music, External Paging, Relays

Feature Name	Feature Data		
Background Music (BGM)			
Music on Hold			
External Page Zone 1			
Ring Over All Call			
External Page Zone 2			
BGM to Ext. Zones			
Interrupted Ring Relays			
Page/Music Volume			
Relay 01 Owner			
Relay 02 Owner			

To enter Program 7 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 7.
3. To accept the displayed data: #.

OR

- To change the displayed data: Dial data + #.
*To erase data before pressing #: Press *.*
4. Repeat step 3 for all data.
If you finish and do not see, "SAVE TO EXIT": SAVE.
 5. Select an option:
 - To enter another program: Press its key.
 - To exit program mode: SAVE.

Program 8 - System Messages

Message No.	Messages												
600													
601													
602													
603													
604													
605													
606													
607													
608													
609													
610													
611													
612													
613													
614													
615													

To enter Program 8 data:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 8.

3. Dial Message number + #.

4. To accept the displayed data: #.

OR

To erase displayed data: Press * + Enter new message (see below) or press # and go to step 3.

OR

To changed the displayed data: Enter entire message + #.

To enter message:

a. Press dialpad button for desired letter or number. To enter a blank space, Q, or Z: Press 0.

b. To make a letter appear: Dial the number (1, 2, or 3) that corresponds to the letter's position on the button (e.g. dial 1 if you want the first letter).

OR

To make a number appear: Dial 4.

Note: To make a blank space, Q, or Z appear: Dial 1, 2, or 3, respectively.

c. Repeat a-b for all characters (to erase previous character: LAST).

5. Repeat steps 3-4 for all messages.

6. Select an option:

- To exit Program 8: SAVE.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE twice.

Program 10 - Line Port Characteristics

Line Number	Circuit Type	Line Gain	PBX Line	Side Tone Test	Name																				
01																									
02																									
03																									
04																									
05																									
06																									
07																									
08																									
09																									
10																									
11																									
12																									
13																									
14																									
15																									
16																									
17																									
18																									
19																									
20																									
21																									
22																									
23																									
24																									

Cont'd next page

Program 10 - Line Port Characteristics (cont'd)

To enter Program 10 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 10.
3. Dial Line number + #.
4. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

- *To erase data before pressing #: Press *.*

- *To enter circuit type X: DIAL + dial X.*

- *To enter a name:*

a. Press dialpad button for desired character. To enter a blank space, Q, or Z: Press 0.

b. To make a letter appear: Dial the number (1, 2, or 3) that corresponds to the letter's position on the button (e.g. dial 1 if you want the first letter).

OR

To make a number appear: Dial 4.

Note: *To make a blank space, Q, or Z appear: Dial 1, 2, or 3, respectively.*

c. Repeat a-b for all characters (to erase previous character: LAST).

5. Repeat step 4 for all data.

If you finish and do not see, "LINE NO.": SAVE.

6. Select an option:

- *To program another line: Go to step 3.*

- *To exit Program 10: SAVE.*

- *To enter another program after exiting: Press its key.*

- *To exit program mode: SAVE twice.*

Program 11 - Line Groups

Group Number	Line Members												
90													
91													
92													
93													
94													
95													
96													
97													
98													

To enter Program 11 data:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 11.

3. Dial Group number + #.

4. To accept the displayed data: #.

OR

To enter or change the displayed data: Dial data + #.

*- To erase data before pressing #: Press *.*

*- To erase a line from the group, dial *. Dialing * for the first member of the group erases the entire group.*

5. Repeat step 4 for all data in group.

6. Press SAVE.

7. Select an option:

- To program another line group: Go to step 3.

- To exit Program 11: SAVE.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE twice.

Program 12 - Line Features

Line Number	CPG (Call Pickup Group)	TR (Toll Restriction)	DTD (Direct Termination Day)	DTN (Direct Termination Night)	COS (Class Of Service)
01					
02					
03					
04					
05					
06					
07					
08					
09					
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					

Cont'd next page

Program 12 - Line Features (cont'd)

To enter Program 12 data:

1. Enter program mode.
+ 775312 + #.
2. Press key 12.
3. Dial Line number + #.
4. Dial feature's abbreviation + #.
5. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

- To accept DTD or DTN data, you may have to press SAVE instead.

*- To erase data before pressing #: Press *.*

6. Repeat steps 4-5 for all features.

7. Press SAVE.

8. Select an option:

- To enter data for another line: Dial Y + go to step 3.

- To exit Program 12: SAVE.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE twice.

Program 14 - Extension Port Characteristics

Port Number	Extension Number	Circuit Type	DSS Owner	DSS Block	Name (16 characters, maximum)
00					
01					
02					
03					
04					
05					
06					
07					
08					
09					
10					
11					
12					
13					
14					
15					
16					
17					
18					
19					
20					
21					
22					
23					
24					
25					
26					
27					
28					
29					
30					
31					
32					
33					
34					
35					

* **Note:** A DSS console cannot be installed in an Expansion Cabinet.

Cont'd next page

Program 14 - Extension Port Characteristics (cont'd)

Port Number	Extension Number	Circuit Type	DSS Owner	DSS Block	Name (16 characters, maximum)
36					
37					
38					
39					
40					
41					
42					
43					
44					
45					
46					
47					
48					
49					
50					
51					
52					
53					
54					
55					
56					
57					
58					
59					
60					
61					
62					
63					
64					
65					
66					
67					
68					
69					
70					
71					

* **Note:** A DSS console cannot be installed in an Expansion Cabinet.

Program 14 - Extension Port Characteristics (cont'd)

To enter Program 14 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 14.
3. Dial Port number + #.
4. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

- *To erase data before pressing #: Press *.*
- *To enter circuit X: DIAL + dial X.*
- *To enter circuit Z: DIAL + dial 0.*
- *To enter a letter, number, blank:*
 - *Press dial pad button that has desired character. Zero button=blank, Q, Z (in that order).*
 - *Dial digit (1, 2, 3)=letter's position on button (e.g., dial 1 for 1st letter).*

OR

Dial 4 for the button's number.

- *To erase last character, press LAST.*
- *Repeat above steps for entire message.*

5. Repeat step 4 for all data.
If you finish and do not see, "STN PORT NO.": SAVE.
6. Select an option:
 - *To program a port: Go to step 3.*
 - *To exit Program 14: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

Note: You cannot change the circuit type of the extension from which you are programming; you must use another extension that has program access level 04 or 05.

Program 15 - Programming Access Level

Extension	Program Access Level
300	
301	
302	
303	
304	
305	
306	
307	
308	
309	
310	
311	
312	
313	
314	
315	
316	
317	
318	
319	
320	
321	
322	
323	

Extension	Program Access Level
324	
325	
326	
327	
328	
329	
330	
331	
332	
333	
334	
335	
336	
337	
338	
339	
340	
341	
342	
343	
344	
345	
346	
347	

Extension	Program Access Level
348	
349	
350	
351	
352	
353	
354	
355	
356	
357	
358	
359	
360	
361	
362	
363	
364	
365	
366	
367	
368	
369	
370	
371	

Cont'd next page

Program 15 - Programming Access Level (cont'd)

To enter Program 15 data:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 15.
3. Dial extension + #.
4. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

*- To erase data before pressing #: Press *.*

5. Repeat steps 3-4 for all extensions.
6. Select an option:
 - To exit Program 15: SAVE.*
 - To enter another program after exiting: Press its key.*
 - To exit program mode: SAVE twice.*

Program 16 - Line and Line Group Access

Extension	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Group 90 Access	Group 91 Access	Group 92 Access	Group 93 Access	Group 94 Access	Group 95 Access	
300																											
301																											
302																											
303																											
304																											
305																											
306																											
307																											
308																											
309																											
310																											
311																											
312																											
313																											
314																											
315																											
316																											
317																											
318																											
319																											
320																											
321																											
322																											
323																											
324																											
325																											
326																											
327																											
328																											
329																											
330																											

Cont'd next page

Program 16 - Line and Line Group Access (cont'd)

Extension	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Group 90 Access	Group 91 Access	Group 92 Access	Group 93 Access	Group 94 Access	Group 95 Access	
331																											
332																											
333																											
334																											
335																											
336																											
337																											
338																											
339																											
340																											
341																											
342																											
343																											
344																											
345																											
346																											
347																											
348																											
349																											
350																											
351																											
352																											
353																											
354																											
355																											
356																											
357																											
358																											
359																											
360																											
361																											

Cont'd next page

Program 16 - Line and Line Group Access (cont'd)

Extension	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Line ___ Access	Group 90 Access	Group 91 Access	Group 92 Access	Group 93 Access	Group 94 Access	Group 95 Access
362																								
363																								
364																								
365																								
366																								
367																								
368																								
369																								
370																								
371																								

To enter Program 16 data:

1. Enter program mode.
 - # + dial 775312 + #.
 2. Press key 16.
 3. Dial extension + #.
 - To erase data before pressing #: Press *.
 4. Dial L for line or G for group data.
 5. Dial Line or Group number + #.
 6. To accept the displayed data: #,
- OR**
- To change the displayed data: Dial data + #.
 7. Repeat steps 5-6 for all lines/groups.
 8. Press SAVE.
 9. Select an option:
 - To enter line or group data for same extension: Go to step 4.
 - To enter data for another extension: SAVE + dial Y + go to step 3.
 - To exit Program 16: SAVE twice.
 - To enter another program after exiting: Press its key.
 - To exit program mode: SAVE three times.

Program 17 - Key Assignments

Before you fill in data, either use the Copy and Paste commands to make additional copies of the blank Key Assignment forms for each installed Multibutton phone and DSS Console or print copies of the forms required. There is a form for the phone and the console. Make sure you copy the correct one.

Extension Number	<u>Keypad Phone</u>					
(Dial pad located here)						
HOLD	CONF	MIC/DND	ICM	MSG	HF	

Cont'd next page

Program 17 - Key Assignments (cont'd)

Extension Number

DSS Console

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

--	--	--	--	--	--	--	--	--	--

Cont'd next page

Program 17 - Key Assignments (cont'd)

To enter Program 17 data:

1. Enter program mode.
 - # + dial 775312 + #.
 - *If you are programming assignments for a DSS Console, you must program from the phone assigned to the console.*
2. Press key 17 (HOLD).
 - You see "DEST ICM NO:" (i.e., destination extension).*
3. Dial extension (XXX) to be programmed + #.
 - You see "SOURCE:" (i.e., source extension). If you are programming assignments for your DSS Console, enter your extension number.*
4. To program the keys at extension XXX: Dial extension (XXX) again + #.

OR

To copy keys from extension YYY to XXX: Dial YYY + # + go to step 8 if you do not need to change individual keys after you copy; otherwise, go to step 5.

- *This procedure does not copy Speed Dial (stored) numbers, Ring Assign. (Program 18 [III]), or Line Access (Program 16).*
 - *If you are programming assignments for your DSS Console, enter your extension number.*
5. Press key you wish to program.
 - *For DSS Consoles, press DSS Console key.*
 6. To accept the displayed data: #.

OR

To change the displayed data: Dial key data + #.

Remember: To dial "Z", dial 0 (zero).

7. Repeat steps 5-6 for other keys.
8. Press SAVE and select an option:
 - *To program another extension: Dial Y + go to step 3.*
 - *To exit Program 17: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

Program 18 - Extension Features (Part I)

Extension	DND (Do Not Disturb)	COS (Class of Service)	RG (Ring Group)	CPG (Call Pickup Group)	PRG (Privacy Release Group)	OHR (Off-Hook Ring)	BLF (DSS/BLF Lamps)	LDU (Line Dial-Up)	PZ (Page Zone Member)	SO (Station Operator)	SDB (Speed Dial Block)	VX (Voice Mail)	DS (Data set)	DB (Door Box) - Alert 1	DB (Door Box) - Alert 2	DB (Door Box) - Alert 3	DB (Door Box) - Alert 4
300																	
301																	
302																	
303																	
304																	
305																	
306																	
307																	
308																	
309																	
310																	
311																	
312																	
313																	
314																	
315																	
316																	
317																	
318																	
319																	
320																	
321																	
322																	
323																	
324																	
325																	
326																	
327																	
328																	
329																	
330																	

Program 18 - Extension Features (Part I) (cont'd)

Extension	DND (Do Not Disturb)	COS (Class of Service)	RG (Ring Group)	CPG (Call Pickup Group)	PRG (Privacy Release Group)	OHR (Off-Hook Ring)	BLF (DSS/BLF Lamps)	LDU (Line Dial-Up)	PZ (Page Zone Member)	SO (Station Operator)	SDB (Speed Dial Block)	VX (Voice Mail)	DS (Data set)	DB (Door Box) - Alert 1	DB (Door Box) - Alert 2	DB (Door Box) - Alert 3	DB (Door Box) - Alert 4
331																	
332																	
333																	
334																	
335																	
336																	
337																	
338																	
339																	
340																	
341																	
342																	
343																	
344																	
345																	
346																	
347																	
348																	
349																	
350																	
351																	
352																	
353																	
354																	
355																	
356																	
357																	
358																	
359																	
360																	
361																	

Program 18 - Extension Features (Part I) (cont'd)

Extension	DND (Do Not Disturb)	COS (Class of Service)	RG (Ring Group)	CPG (Call Pickup Group)	PRG (Privacy Release Group)	OHR (Off-Hook Ring)	BLF (DSS/BLF Lamps)	LDU (Line Dial-Up)	PZ (Page Zone Member)	SO (Station Operator)	SDB (Speed Dial Block)	VX (Voice Mail)	DS (Data set)	DB (Door Box) - Alert 1	DB (Door Box) - Alert 2	DB (Door Box) - Alert 3	DB (Door Box) - Alert 4
362																	
363																	
364																	
365																	
366																	
367																	
368																	
369																	
370																	
371																	

To enter Program 18 (Part I) data:

1. Enter program mode.
+ dial 775312 + #.
 2. Press key 18 (CONF).
 3. Dial extension + #.
 4. Dial feature abbreviation + #.
To dial PZ: Dial P0.
 5. To accept the displayed data: #.
- OR**
- To change data: Dial data + #.
- *To erase a data entry before you press #: Press *.*
 - *To accept the SO (station operator) data, you may have to press SAVE instead.*
6. Repeat steps 4-5 for all features.
 7. Press SAVE or Go to step 4 in a Program 18 (Part II) procedure.
 8. Select an option:
 - *To enter Part I data for another extension: Dial Y + go to step 3.*
 - *To exit Program 18: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

Program 18 - Extension Features (Part II)

Before you fill in data, either use the Copy and Paste commands to make additional copies of the blank Extension Feature forms for each installed extension or print copies of the blank forms as needed.

Extension: _____

Feature	Y/N
HS (Headset)	
VA (Voice-Announce Calls)	
VP (Voice Page Thru Spkr)	
VO (Whisper Page)	
RLP (Ringing Line Pref.)	

Feature	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	Line #	
RA (Ringing Assignment)																				
NR (Night Ringing)																				
DRA (Direct Ringing Assign.)																				
PLA (Prime Line Assign.)																				

Personal Speed Dial Numbers	
Bin 50:	
Bin 51:	
Bin 52:	
Bin 53:	
Bin 54:	
Bin 55:	
Bin 56:	
Bin 57:	
Bin 58:	
Bin 59:	
Bin 20:	
Bin 21:	
Bin 22:	
Bin 23:	
Bin 24:	
Bin 25:	
Bin 26:	
Bin 27:	
Bin 28:	
Bin 29:	

Key 1:	
Key 2:	
Key 3:	
Key 4:	
Key 5:	
Key 6:	
Key 7:	
Key 8:	
Key 9:	
Key 10:	
Key 11:	
Key 12:	

Key 13:	
Key 14:	
Key 15:	
Key 16:	
Key 17:	
Key 18:	
Key 19:	
Key 20:	
Key 21:	
Key 22:	
Key 23:	
Key 24:	

Program 18, Part II (cont'd)

Direct Station Selection (and Call Coverage) and Hotline Layout

Keys 1-15 are Direct Station Selection keys. The Call Coverage and Hotline keys can be anywhere, depending on how they are assigned in Program 17. You can use the DSS procedure below to change the extension associated with a DSS or Call Coverage key.

Keyset Phone

<input type="text"/>	<input type="text"/>
<input type="text"/>	<input type="text"/>
<input type="text"/>	<input type="text"/>
<input type="text"/>	<input type="text"/>
<input type="text"/>	<input type="text"/>

(Dial pad located here)

<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>
HOLD	CONF	MIC/DND	ICM	MSG	HF
<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>

To enter Program 18 data for HS, VA, VP, VO, RLP:

1. Enter the program mode.
+ dial 775312 + #.
2. Press key 18 (CONF).
3. Dial extension + #.
4. Dial feature abbreviation + #.
5. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

6. Select an option:
 - To program another feature: Go to step 4 (in any Program 18 procedure).
 - To program another extension: SAVE + dial Y + go to step 3 (in any Program 18 procedure).
 - To exit Program 18: SAVE twice.
 - To enter another program after exiting: Press its key.
 - To exit program mode: SAVE three times.

Cont'd next page

Program 18, Part II (cont'd)

To enter Program 18 data for RA, NR, DRA, PLA:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 18 (CONF).

3. Dial extension + #.

4. Dial feature abbreviation + #.

The Line keys you can program light steadily or flash. Steady means the feature is disabled, flashing means it is enabled.

5. Dial a line number.

OR

Press a Line key.

6. To change or enter data: Dial data (Y)es or (N)o, press #.

7. Repeat steps 5-6 for all lines.

8. Select an option:

*- To program another feature for same extension: SAVE + go to step 4
(in any Program 18 procedure).*

*- To program another extension: SAVE twice + dial Y + go to step 3
(in any Program 18 procedure).*

- To exit Program 18: SAVE three times.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE four times.

To enter Program 18 data for Personal Speed Dial (SD):

1. Enter the program mode.

+ dial 775312 + #.

2. Press key 18 (CONF).

3. Dial extension + #.

4. Dial SD + #.

5. Dial bin number + #.

OR

Press lit bin key (to make a SD bin keys, see Program 17).

6. If you can store a name: Enter name + #. Or, skip to step 7.

To enter a letter, number, blank:

- Press dial pad button that has desired character. Zero button=blank, Q, Z (in that order).

- Dial digit (1, 2, 3)=letter's position on button (e.g., dial 1 for 1st letter).

OR

Dial 4 for the button's number.

- To erase last character, press LAST.

- Repeat above steps for entire message.

7. Store a line as follows: Press a Line key or (Dial line number + #).

- Reorder tone means you cannot store that line. Go to step 4.

- To store Intercom feature codes: Press ICM in step 7, dial codes in step 8.

8. To accept the displayed data: # + go to step 5.

OR

To change the displayed data: Dial telephone number + #.

- You can store any number allowed by the toll level of the extension you program from.

Numbers longer than 16 digits flow to the next bin.

- To enter a pause: HOLD.

Cont'd next page

Program 18, Part II (cont'd)

- To enter a Flash, press MSG, or to enter a Delay, press DIAL. These options are only available with software versions AUX Module 02.10/Base 02.00 and higher.
- To enter *: DIAL + press *.
- To enter #: DIAL + press #.

9. Select an option:

- To program more bins: Go to step 5.
- To program another feature: SAVE + go to step 4 in any Program 18.
- To program another extension: SAVE twice + dial Y + go to step 3.
- To exit Program 18: SAVE three times.
 - To enter another program after exiting: Press its key.
- To exit program mode: SAVE four times.

To enter Program 18 data for DSS:

1. Enter the program mode.

+ dial 775312 + #.

2. Press key 18 (CONF).

3. Dial extension + #.

4. Dial DSS or HL + #.

DSS keys (1-15) flash, any Call Coverage and Hotline keys flash.

5. Press a flashing key.

6. To accept the displayed data: #.

OR

To change the displayed data: Dial data + #.

7. Repeat steps 5-6 for all DSS keys you wish to program.

8. Select an option:

- To program another extension for DSS: SAVE twice + dial Y + go to step 3 (in any Program 18 procedure).
- To program another feature for same extension: SAVE + go to step 4 (in any Program 18 procedure).
- To exit Program 18: SAVE three times.
 - To enter another program after exiting: Press its key.
- To exit program mode: SAVE four times.

Cont'd next page

Program 18, Part II (cont'd)

To enter Program 18 data for System Speed Dial (SD):

1. Enter the program mode.

+ dial 775312 + #.

2. Press key 18 (CONF).

3. Dial the number of the extension you are programming from + #.

4. Dial SD + #.

5. Dial bin number + #.

6. If you can store a name: Enter name + #. Or skip to step 7.

To enter a letter, number, blank:

- Press dial pad button that has desired character. Zero button=blank, Q, Z (in that order).

- Dial digit (1, 2, 3)=letter's position on button (e.g., dial 1 for 1st letter).

OR

Dial 4 for the button's number.

- To erase last character, press LAST.

- Repeat above steps for entire message.

7. Store a line: Press a Line key or (Dial line number + #).

- Reorder tone means you cannot store that line. Go to step 4.

- To store Intercom feature codes: Press ICM in step 7, dial codes in step 8.

8. To accept the displayed data: # + go to step 5.

OR

To change the displayed data: Dial telephone number + #.

- You can store any outside number allowed by the toll restriction level of the extension you program from. Numbers longer than 16 digits automatically flow to the next bin.

- To enter a pause: HOLD.

- To enter a Flash, press MSG, or to enter a Delay, press DIAL. These options are only available available with software versions AUX Module 02.10/Base 02.00 and higher.

*- To enter *: DIAL + dial *.*

- To enter #: DIAL + dial #.

9. Select an option:

- To program more bins: Go to step 5.

- To program another feature: SAVE + go to step 4 (in any Program 18 procedure).

- To program another extension: SAVE twice + dial Y + go to step 3 (in any Program 18 procedure).

- To exit Program 18: SAVE three times.

- To enter another program after exiting: Press its key.

- To exit program mode: SAVE four times.

Program 19 - Extension Hunt Groups

Before you fill in data, either use the Copy and Paste commands to make additional copies of the blank Circular/Terminal or UCD/ACD Hunt Group form for each such group you wish to program or print and copy the forms as needed.

Form for Circular/Terminal Hunt Group

Group Name: _____

Member Extension	Hunt Type

Member Extension	Hunt Type

Member Extension	Hunt Type

To enter Program 19 data for Circular or Terminal Hunt (types 01, 02, 03):

- Enter program mode.
 - # + dial 775312 + #.
- Press key 19 (MIC/DND).
- Dial 01, 02, or 03 (it doesn't matter).
- Dial Member Extension + #.
- Dial Hunt Type + #.
- Repeat steps 4-5 for all Member Extension
- Select an option:
 - To program another group: # until you see "HUNT TYPE -" + Go to step 3 in any Program 19 procedure.
 - To exit Program 19: SAVE.
 - To enter another program after exiting: Press its key.
 - To exit program mode: SAVE twice.

Note: To accept the displayed data in any step: #.

To delete a member of a Circular or Terminal group:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 19 (MIC/DND).
3. Dial 01, 02, or 03 (it doesn't matter).
4. Dial first Member Extension in group + #.
5. Press # until you see the extension you want to delete.
6. If the extension is the last extension in a Terminal hunt group: Dial 300 + #.

OR

If the extension is in the middle of a group, dial the extension that comes after it + #.

For example, if the group is 304, 305, 306 and you want to delete 305:

- Press # until you see 305 (as explained in step 5).

- Dial 306 + #.

7. Continue as follows:
 - *Press # until you see "HUNT TYPE - ".*
 - *Dial 01, 02, or 03 + #.*
 - *Dial the extension you just deleted + #.*
 - *Dial 00 for Hunt Type + #.*
8. Press SAVE until you exit program mode.

Note: To accept the displayed data in any step: #.

To add a member to a Circular or Terminal Group:

1. Enter program mode.
+ dial 775312 + #.
2. Press key 19 (MIC/DND).
3. Dial 01, 02, or 03 (it doesn't matter).
4. Dial first Member Extension + #.
5. Press # until you see the extension before which you want to add an extension.
For example, if the group is 304, 305, 306 and you want to add 307 before 306: Press # until you see 306.
6. Dial the extension you want to add + #. Dial its Hunt Type + #. Repeat for the extension after it.
To continue with the example set up in step 5: Do step 6 for extension 307, then 306.
7. Press # until you see "HUNT TYPE-".
8. Press SAVE until you exit program mode.

Note: To accept the displayed data in any step: #.

Cont'd next page

Program 19 - Extension Hunt Groups (cont'd)

Form for a UCD/ACD Hunt Group

Before you fill in the data, either use the Cut and Paste commands to make additional copies of the blank forms for each UCD/ACD group you wish to program or print and copy the forms as needed.

Group Name: _____

Hunt Type	Master Extension	Overflow Extension	Supervisor Extension

Member Extension	Hunt Type

Member Extension	Hunt Type

Member Extension	Hunt Type

To enter Program 19 data for UCD/ACD Hunt (type 04, 05):

1. Enter program mode.
+ dial 775312 + #.
2. Press key 19 (MIC/DND).
3. Dial Hunt Type + #.
4. Dial Master Extension + #.
5. For type 04: Go to step 6.
For type 05: Dial Overflow + #.
6. Press # to move past "MASTER EXT." prompt.

OR

- To delete a group: Dial * + SAVE + Go to step 10.
7. Dial a Member Extension when you see UCD MEMBER + #.
- To move past a member: #.
- To delete a member: Dial *.

Program 19 - Extension Hunt Groups (cont'd)

8. Repeat step 7 for all members.
9. Press SAVE.
10. Select an option:
 - *To program another group: Go to step 3 in any Program 19 procedure.*
 - *To exit Program 19: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

Note: To accept the displayed data in any step: #.

To enter Program 19 data for ACD Supervisor:

1. Enter program mode.
 - # + dial 775312 + #.*
2. Press key 19 (MIC/DND).
3. Dial 00 for Hunt Type + #.
4. Dial Master Extension for Supervisor's group + #.
 - You see "UCD MEMBER."*
5. Dial Supervisor Extension + #.
 - This step automatically places the Supervisor Extension in the associated UCD group.*
6. Select an option:
 - *To program another Supervisor, go to step 3.*
 - *To exit Program 19: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

To delete an ACD Supervisor

1. Enter program mode.
 - # + dial 775312 + #.*
2. Press key 19 (MIC/DND).
3. Dial Hunt Type for Supervisor's group + #.
4. Dial Master Extension for Supervisor's group + #.
5. Press # until you see Supervisor's Extension.
6. Press *.
7. Press SAVE.
8. Select an option:
 - *To delete more Supervisor Extensions: Go to step 3.*
 - *To exit Program 19: SAVE.*
 - *To enter another program after exiting: Press its key.*
 - *To exit program mode: SAVE twice.*

Note: To accept the displayed data in any step: #.

Program 20 - System Initialization

To use Program 20:

1. Enter program mode.

+ dial 775312 + #.

2. Press key 20 (ICM).

3. Dial Y to initialize and wait for the date and time to display. When you see the date and time, this means initialization is complete.

OR

Dial N to exit Program 20 without initialization.

- To enter another program: Press its key.

- To exit program mode: Press SAVE.



**Nitsuko America, Telecom Division
4 Forest Parkway
Shelton, CT 06484**

TEL: 203-926-5400
FAX: 203-929-0535

Other Important Telephone Numbers

Sales:	203-926-5450
Customer Service:.....	203-926-5444
Customer Service FAX:.....	203-926-5454
Technical Service:	203-925-8801
Discontinued Product Service:	900-990-2541
Technical Training:.....	203-926-5430
Emergency Technical Service (After Hours):	203-929-7920

(Excludes discontinued products)



Digital System Program Record Form

Part No. N1872PRF04
Issue 1-0, June 1996
Printed in U.S.A.

This manual has been developed by Nitsuko America. It is intended for the use of its customers and service personnel and should be read in its entirety before attempting to install or program the system. Any comments or suggestions for improving this manual would be appreciated. Forward your remarks to:

Nitsuko America, Telecom Division
4 Forest Parkway
Shelton, CT 06484

Attention: Manager, Technical Publications

Nothing contained in this manual shall be deemed to be, and this manual does not constitute, a warranty of, or representation with respect to, any of the equipment covered. This manual is subject to change without notice and Nitsuko America has no obligation to provide any updates or corrections to this manual. Further, Nitsuko America also reserves the right, without prior notice, to make changes in equipment design or components as it deems appropriate. No representation is made that this manual is complete or accurate in all respects and Nitsuko America shall not be liable for any errors or omissions. In no event shall Nitsuko America be liable for any incidental or consequential damages in connection with the use of this manual. This document contains proprietary information that is protected by copyright. All rights are reserved. No part of this document may be photocopied or reproduced without prior written consent of Nitsuko America.

© 1996 by Nitsuko America. All Rights Reserved.
Printed in U.S.A.